Creo Inc.
A subsidiary of Kodak
3700 Gilmore Way
Burnaby, B.C., Canada
V5G 4M1
Tel: 1.604.451.2700
Fax: 1.604.437.9891

Request support:
ecentral.creo.com

www.creo.com

Internal: 731-00634A-EN Rev A
Release date: 01 September 2005

Procedure

Using netconf to Configure Brisque 5.x Adapter

This procedure explains how to use the **netconf** utility to configure the correct adapter in Brisque® 5.x.

1. Log in to UNIX® as root user with ripro password
   login: `root`
   root password: `ripro`
2. Type `# lsip.sh`. The following appears:

```
Int type   IP_address  Mask   DNS  Gateway  Domain      Speed Selected
-------------------------------------------------------------------------------
en0       10.2.27.30   255.255.255.0  10.2.27.254  Auto_Negotiation    GIGABIT
en1                                   10.2.27.254  Auto_Negotiation    100BT
en2       192.9.100.1  255.255.255.0  10.2.27.254  Auto_Negotiation    100BT
```

3. From the list, identify the correct **entx** board—it's the one with the current Brisque IP address.
   Type: `# cd /usr/local/es`
   `# netconf`
4. From the menu, select **Configure Adapter** and press **Enter**

```
------ NetConf -------
Configure Adapter
Configure Zones
----------------------
Quit
----------------------
```

5. In the following menu, use the arrow keys to select the correct **entx** board. Press the <space bar> to enable/disable the board.
   Note: Only the correct board should have a **+** (plus sign).

```
------------ AppleTalk Network Setup ----------------------------------------
--   Interface Start End Node Default Zone            [Additional Zones]    --
--      +et0    Automatic configuration                                     --
--       et1    Automatic configuration                                     --
--       et2    Automatic configuration                                     --
-------------------------------------------------------------------------------
--                                                                           --
--                                                                           --
--                                                                           --
--                                                                           --
--                                                                           --
--                                                                           --
--                                                 Cancel          Ok        --
-------------------------------------------------------------------------------
 <RET>=config, ' '=(de)activate, 'a'=auto on/off, '?'=help         1/3 adapter
```

6. Use <Tab> to select **OK**
7. Press <Enter> twice
8. Use the <down arrow> to select **Quit**
9. Restart Appletalk. Type: `# res`
   The following appears:

```
Configuration of 'atalk.conf' file...
"/scitex/version/usr/local/es/conf" is configuration directory.
"atalk.conf" configured.        Parameter "ipaddress=10.2.27.30" defined.
"atalk.conf" configured.        Parameter "nohomedir" added.
"atalk.conf_valid" configured.  Parameter "ipaddress=10.2.27.30" defined.
"atalk.conf_valid" configured.  Parameter "nohomedir" added.
cat: cannot open /usr/local/es/conf/afpipaccess
#
```

About Kodak Graphic Communications Group (GCG)

The leading provider of graphic communications solutions worldwide, Kodak's Graphic Communications Group (GCG) offers image capture systems; professional color, copydot, and high-speed document scanning systems; inkjet printing and proofing systems; workflow and color management software; thermal imaging devices for film, plates, and proofs; high-quality proofing media, printing plates, and recording film; on-demand color and black-and-white printing systems; data storage products; and professional services. Creo joined the GCG in June 2005, when it became a wholly owned subsidiary of Kodak. With corporate headquarters located in Rochester, N.Y., Kodak (NYSE: EK) had sales of $13.5 billion in 2004 and is committed to a digitally oriented growth strategy.

© 2005 Kodak. The Creo product names mentioned in this document are trademarks or service marks of Creo Inc., a subsidiary of Kodak, and may be registered in certain jurisdictions. Other company and brand, product, and service names are for identification purposes only and may be trademarks or registered trademarks of their respective holders. Data subject to change without notice.