Output Update
(Upd_Brisque4_97_Output - 4.0.97.3)

(Size 53550KB)

Read Me Contents:

A. Who should load this update?
B. What this update includes?
C. Minimum Requirements
D. Loading Instructions

A. Who should load this update?

Mandatory for all Brisque Version 4.0.97 connected to any output device including Screen2Go.
Mandatory for any customers using the LRS, Step One, or PCF Applications on top of Version 4.0.97
Mandatory for any customers using the Brisque's Versioning abilities.

B. What this update includes?

This update combine the output related updates previously released and appear in the list below, also it is contain the following corrections:

1. Correction for LotemQuantum (divide by 32)
2. Correction for Vc175r94c for Trendsetter & Quantum - Patterns problems
3. New JTlouncher - to correct Queue Manager sequence mainly in BitMap workflow
4. QServer correction - to avoid intermittent application shutdown during Expose.
5. Correction for Error 7155 with 2xTSPs

List of updates replaced by the new output updates:

Upd_PlateExpInv update – 4.0.97.1 (previously was available on 4.0.97 CD2)

To fix page inventory problems in Plate Expose

Upd_Brisque4_97_Versioning update - 4.0.97.17 (previously was available on 4.0.97 CD2)

Was mandatory to support Versioning on version 4.0.97

Upd_Brisque4_97_Bitmap - 4.0.97.26

Corrections for:

1. Include all the corrections from the previous BitMap updates (4.0.97.18 and 4.0.97.23) 4.0.97.18 was mandatory to improve 1-bit TIFF direct Expose on top of 4.0.97.4.0.97.23 correction were:
   • Support direct expose of Allegro 1bitTiff files.
   • Endless loop while using 90 deg. rotate.
2. Correction for TSP errors 7106, 7125 while using plate expose on Trendsetters, mainly happened with F50 platform.
3. Correction for very high resolution problem (400) on Dolev800V (for Jura)

Upd_Brisque4_97_Packaging - 4.0.97.21

Corrections for:

1. Replace the previous Packaging update (4.0.97.19):
   "Support for LRS and Packaging workflow on top of Version 4.0.97. The Version 4.0.97 + the 4.0.97.19 update was the first released version supporting these options."
2. LRS Workflow - A thin line appears on plate or film. The lines appear exactly when files end or start, can be both around and across the plate or film. The lines do not appear on Screen2Go files.
3. LRS Workflow - creating file with rotate pages and step & repeart, the pkg.job shown in preview with missing pages. Improof was fine.

Upd_Brisque4_97_Spectrum - 4.0.97.8

Mandatory for all Brisque to Trendsetter / Spectrum direct installations including Trendsetters that only output plates and includes the following corrections:

1. Fix hanging problem during Proof, mainly with 43P-150 (Tiger 2)
2. Fix for retraces problem during Proof.
3. Improves the overall Proof performance.

Upd_Brisque4_97_Staccato - 4.0.97.5

Mandatory for all Brisque to LotemQuantum/Trendsetter using Staccato (FM_Screening) option.

1. Include all the corrections from the previous Staccato update (4.0.97.3)
   - Tone Rep curve was working in opposite values.
   - "Strengthens" for Lotem Quantum includes HexaChrome files, to avoid banding problem on print.
   - Cyclic for spot colors, to avoid banding problem on print.
2. Plate Expose fail with 7155 Error while using Staccato with certain plate sizes.

C. Minimum Requirements:

Should be loaded on top of Brisque version 4.0.97 with the mandatory updates **Upd_Brisque4_97_1 (4.0.97.18)** and **Upd_Brisque4_97_ResetBoard (4.0.97.4)**, both exist on Version 4.0.97 2 of 2 CD and are automatically loaded during the Version 4.0.97 installation process.

Select **Station Info > More Info** and make sure you have the following packages prior to installation:

Upd_Brisque4_97_1 (4.0.97.18)
Upd_Brisque4_97_ResetBoard (4.0.97.4)

D. Loading Instructions

Notes:

- If you've previously downloaded the **update.tar** script and created the **.updates** folder, start at **step 3**.
- Before you start, please check if the Brisque installed with updates that are not in the Output update list (see above) and reinstall them at the end of this procedure.

1. Reload Version 4.0.97 using **scismit** >> **Software Handinlg** >> **Loading Full Version.**
2. Create a folder on the Brisque named **.updates** under the **FIRST** dataVolumes (example: **/dataVolumes/brisque1.1.0/.updates**
   Note: In order to see the **.updates** folder from the Brisque, click View and make sure Show Hidden Objects is selected (or Ctrl + S).
3. Copy/download the script **update.tar** from: ftp://ftpcsa.creo.com/brisque/download/V4/Updates/4.0.97/script/ into the **.updates** folder.
4. Copy/download **Upd_Brisque4_97_Output_3.tar** from: ftp://ftpcsa.creo.com/brisque/download/V4/Updates/4.0.97/TestUpdates/Output-3 into the **.updates** folder.
5. Logout from the Brisque application.
6. Login as root/ripro.
   Note: If you've previously installed the **update.tar** script, continue with **step 7**.
7. Type: ***tar -xvf /dataVolumes/brisque1.1.0/.updates/update.tar*** and hit **Enter**.
8. Type: ***update.sh*** and hit **Enter**.
9. Type a period (**.**) in **INPUT device** field and hit **Enter**.
10. Hit [**F4**], select **Upd_Brisque4_97_Output** and hit **Enter**.
11. Hit **Enter** twice.
12. After the **OK** message, hit the [**F10**] key.
13. Type: **y** and hit **Enter** for automatic reboot.

After rebooting, login as ***cdesci*** and go to **Station Info** --> **More Info** to confirm that:
Upd_Brisque4_97_Output.obj 4.0.97.3 is listed.