Customer
Installation Guide

English

Software Migration From Brisque version 4.0 to 4.1

653-00422A

www.creo.com

Copyright

Copyright © 2003 Creo Inc. All rights reserved.

No copying, distribution, publication, modification, or incorporation of this document, in whole or part, is permitted without the express written permission of Creo. In the event of any permitted copying, distribution, publication, modification, or incorporation of this document, no changes in or deletion of author attribution, trademark legend, or copyright notice shall be made.

No part of this document may be reproduced, stored in a retrieval system, published, used for commercial exploitation, or transmitted, in any form by any means, electronic, mechanical, photocopying, recording, or otherwise, without the express written permission of Creo Inc.

This document is also distributed in Adobe Systems Incorporated's PDF (Portable Document Format). You may reproduce the document from the PDF file for internal use. Copies produced from the PDF file must be reproduced in whole.

Trademarks

The Creo wordmark, Creo logo, and the names of the Creo products and services referred to in this document are trademarks of Creo Inc.

Adobe, Acrobat, and the Acrobat logo are registered trademarks of Adobe Systems Incorporated, and are registered in the U.S. Patents and Trademark Office and may be registered in other jurisdictions.

Apple, AppleTalk, AppleShare, EtherTalk, LocalTalk, Macintosh, and LaserWriter are trademarks of Apple Computer, Inc.

Microsoft, Windows, Windows 2000, and Windows NT are trademarks or registered trademarks of Microsoft Corp.

Xerox is a registered trademark of Xerox Corp.

Other brand or product names are the trademarks or registered trademarks of their respective owners.

FCC Compliance

The Creo equipment referred to in this document complies with the requirements in Part 15 of FCC Rules for a Class A computing device. Operation of the Creo equipment in a residential area may cause unacceptable interference to radio and TV reception, requiring the operator to take whatever steps are necessary to correct the interference.

Limitation of Liability

The product, software or services are being provided on an "as is" and "as available" basis. Except as may be stated specifically in your contract, Creo Inc. expressly disclaims all warranties of any kind, whether express or implied, including, but not limited to, any implied warranties of merchantability, fitness for a particular purpose and non-infringement.

You understand and agree that Creo Inc. shall not be liable for any direct, indirect, incidental, special, consequential or exemplary damages, including but not limited to, damages for loss of profits, goodwill, use, data or other intangible losses (even if Creo has been advised of the possibility of such damages), resulting from: (i) the use or the inability to use the product or software; (ii) the cost of procurement of substitute goods and services resulting from any products, goods, data, software, information or services purchased; (iii) unauthorized access to or alteration of your products, software or data; (iv) statements or conduct of any third party; (v) any other matter relating to the product, software, or services.

The text and drawings herein are for illustration and reference only. The specifications on which they are based are subject to change. Creo Inc. may, at any time and without notice, make changes to this document. Creo Inc., for itself and on behalf of its subsidiaries, assumes no liability for technical or editorial errors or omissions made herein, and shall not be liable for incidental, consequential, indirect, or special damages, including, without limitation, loss of use, loss or alteration of data, delays, or lost profits or savings arising from the use of this document.

Patents

This product is covered by one or more of the following U.S. patents:

RE37,376	5,283,140	5,517,359	5,699,740	5,969,872	6,134,393	6,283,589
4,456,924	5,291,273	5,519,852	5,708,736	5,973,801	6,136,509	6,295,076
4,500,919	5,323,248	5,526,143	5,713,287	5,986,819	6,137,580	6,299,572
4,558,302	5,325,217	5,532,728	5,742,743	5,995,475	6,147,789	6,318,266
4,743,091	5,339,176	5,561,691	5,764,374	5,996,499	6,158,345	6,340,817
4,992,864	5,343,059	5,568,595	5,764,381	5,998,067	6,159,659	6,352,816
5,049,901	5,355,446	5,576,754	5,771,794	6,003,442	6,164,637	6,353,216
5,079,721	5,359,451	5,579,115	5,785,309	6,014,471	6,180,325	6,366,339
5,081,617	5,359,458	5,592,309	5,802,034	6,016,752	6,181,362	6,371,026
5,103,407	5,367,360	5,594,556	5,813,346	6,031,932	6,181,439	6,377,739
5,111,308	5,384,648	5,600,448	5,818,498	6,043,865	6,186,068	6,387,597
5,113,249	5,384,899	5,608,822	5,854,883	6,060,208	6,189,452	6,396,422
5,122,871	5,412,491	5,615,282	5,861,904	6,063,528	6,191,882	6,396,618
5,124,547	5,412,737	5,625,766	5,861,992	6,063,546	6,204,874	6,407,849
5,132,723	5,420,702	5,636,330	5,875,288	6,072,518	6,208,369	6,414,755
5,150,225	5,420,722	5,649,220	5,894,342	6,090,529	6,214,276	6,422,801
5,153,769	5,459,505	5,650,076	5,900,981	6,096,461	6,217,965	6,435,091
5,155,782	5,473,733	5,652,804	5,934,196	6,098,544	6,252,522	
5,157,516	5,481,379	5,680,129	5,942,137	6,107,011	6,260,482	
5,208,818	5,488,906	5,691,823	5,946,426	6,112,663	6,266,080	
5,208,888	5,497,252	5,691,828	5,947,028	6,115,056	6,266,134	
5,247,174	5,508,828	5,696,393	5,958,647	6,121,996	6,267,054	
5,249,067	5,509,561	5,699,174	5,966,504	6,130,702	6,268,948	

Creo Inc.
3700 Gilmore Way
Burnaby, B.C., Canada
V5G 4M1
Tel: 1-604-451-2700
Fax: 1-604-437-9891

http://www.creo.com

653-00422A

Revised May 2003

Software Migration From Brisque version 4.0 to 4.1

Read Me First 2
Kit Contents 3
Upgrade From Brisque version 4.0.97.xx to 4.1 4

Read Me First

This document describes the upgrade from Brisque version 4.0.97.xx to Brisque version 4.1 which includes the upgrade of AIX 4.3.3 + ML08 to AIX 4.3.3 + ML10.

The migration procedure starts with a pre-installation CD, containing the **v41ready** program.

The v41ready program consists of two major consecutive operations:

- Validation of software and hardware prerequisites for user installation
- Preparation and initiation of a fully automated loading of version 4.1

During the validation procedure, certain system checks may affect the progress of the installation performed. If any problems are detected, you will be informed and instructed on how to proceed.



Important: Refer to the **Brisque version 4.1 Additional Updates CD** and corresponding documentation for information regarding the Brisque configuration-specific updates that are available.

Kit Contents

Brisque version 4.1 Support Kit		634-00015A

Includes the following items:

Brisque v4.1 Pre-Installation CD	**#1**	**633-00040A**
Brisque v3>v4.1 Migration diskette	**#2**	**633-00045A**
Brisque AIX Ver 4.3.3 (ML10) CD	**#3**	**633-00041A**
Brisque AIX 4.3.3 add-on (ML10) CD	**#4**	**633-00043A**
Brisque v4.1 Product CD (1 of 2)	**#5**	**633-00046A**
Brisque v4.1 Product CD (2 of 2)	**#6**	**633-00047A**
Brisque v4.1 Additional Updates CD	**#7**	**633-00175A**
Brisque v4.1 Installation diskette		**633-00042A**
Brisque v4.1 Accessories CD		**633-00044A**
Brisque v4.0 Documentation CD		**510V1R381B**

Upgrade From Brisque version 4.0.97.xx to 4.1

Note: Please ensure that 4.0.97.xx is the official version found in the "blue box".

Important: Changes that were made to Brisque defaults will be lost during the upgrade from v4.0 to v4.1. We recommend that you take note of all the parameters and insert them manually once the upgrade is complete.
The preferences are found above File Info in Prefs.

Note: Not all of the kit components are used in this installation.

To upgrade from Brisque version 4.0.97.xx to version 4.1:

1. Insert the **Brisque v4.1 Pre-Installation CD (#1)** into the CD-ROM drive.

   Note: Remember to leave the front door open since the CD will automatically be ejected.

2. Mount the CD-ROM drive using **MountPro** as follows:
   a. From the File Manager panel, on the Launch Pad, open the **MountPro** application.

      The Devices and Remote Station window is displayed.

   b. From the list box, select **Devices**.

      The available devices are displayed in the section below.

   c. Select and mount the CD-ROM drive.
3. From the Launch Pad, open a new File Manager window.
4. On the File Manager window, double-click the **CD0** folder.
5. Double-click the **v41ready** icon.

   The Action Run window is displayed.
6. On the Action Run window, click **OK**.

   The v41ready window is displayed.
7. Follow the on-screen v41ready program instructions. When ready, you will be prompted to insert the **Brisque AIX 4.3.3 add-on (ML10) CD (#4)**.

8. Proceed with the installation and follow the on-screen instructions along with this manual.

The system automatically saves the configuration and reboots. After approximately 4 minutes, the upgrade process begins with the loading of ML-10.



Note: This process takes approximately 25 minutes to complete.

Upon completion, the **Brisque AIX 4.3.3 add-on (ML10) CD (#4)** is automatically ejected.

The following message is displayed on the screen:

```
******************************************************
Please remove "AIX Add-On CD".
Please insert Brisque Product CD 1 and press Enter to
continue...
******************************************************
```

9. Remove the **Brisque AIX 4.3.3 add-on (ML10) CD (#4)** and insert the **Brisque v4.1 Product CD (1 of 2) (#5)**, then press ENTER.



Note: This process takes approximately 20 minutes to complete and may take longer according to the amount of internal or external memory.

Note: Please be aware that during the process the screen will switch to save mode. Press the space bar to refresh the screen.

Note: Remember to leave the front door open since the CD will automatically be ejected.

When ready, the following message is displayed on the screen:

```
******************************************************
Please insert Brisque Product 2 CD and press Enter to
continue...
******************************************************
```

10. Remove the **Brisque v4.1 Product CD (1 of 2) (#5)** and insert the **Brisque v4.1 Product CD (2 of 2) (#6)**, then press ENTER.



Note: This process takes approximately 15 minutes to complete.

After reboot, the Console Login is displayed:

```
AIX Version
(c) Copyrights by IBM and others 1982, 1996
Console Login:
```

11. Remove the **Brisque v4.1 Product CD (2 of 2) (#6).**

The system is loaded with version 4.1 and ready for login as `cdesci`.



Note: You can confirm the installation of the updates by accessing **Station Info>More Info** on Brisque.

The following updates should appear:

- **Upd_Brisque41_76_1.obj** 4.1.76.1
- **Upd_Brisque41_ExposeJRE.obj** 4.1.68.1



Important: Refer to the **Brisque version 4.1 Additional Updates CD** and corresponding documentation for information regarding the Brisque configuration-specific updates that are available.