

Installation:

Macintosh System Specification:

- Macintosh G3 model or higher (USB required)
- Mac OS 9.0 or higher
- ColorSync 3.0 or higher
- USBPrintDriver 1.2 or higher
- 160MB RAM
- 3GB Disk or greater (at least 50MB free for installation)
- Minimum display size of 15 inch

Hardware:

- Connect the Iris iPROOF Printer™ to the USB port
- Connect the Software Protection Device to the USB port

To install Iris iPROOF Software:

- Insert the Iris iPROOF Software CD-ROM
- Double click the Iris iPROOF Software CD-ROM icon
- Read these Iris iPROOF Release Notes for any last minute instructions
- Double click the "Iris iPROOF Installer" icon
- When the installer window appears, click "Continue"
- Read the notes and click "Continue"
- Click "Install"
- Choose your destination folder and click "Install"
- When installation is done, click "Quit"
- You will be notified if your system must be restarted

AdobePS Installer (see the file *AdobePS.pdf* for more information about the AdobePS printer driver):

- To install the AdobePS printer driver on a Macintosh: Double-click the *Macintosh AdobePS Installer* icon on this CD-ROM, and follow the instructions.
- To install the AdobePS printer driver on Windows 95, 98, or NT: Insert this CD-ROM on the Windows computer, run the appropriate installer, and follow the instructions.

ColorSync Profiles:

All ColorSync Profiles that reside in the Iris iPROOF Profiles folder will be removed during installation. Move or copy any desired profiles prior to installation.

Using a PCI USB Adapter Card:

If you are using a PCI USB adapter card in your Macintosh computer to communicate with the Iris iPROOF Printer™, be sure to install the appropriate software update available from Apple Computer.

- For Mac OS 8.6 or greater: install *USB Adapter Card Support Version 1.4.1*.
- For Mac OS 8.5.1: install *USB Adapter Card Support Version 1.2*.



These files can be downloaded from the Apple Computer website at:

http://asu.info.apple.com/swupdates/nsf/artnum/n11543

Known Problems:

With this release of the Iris iPROOF software, there are some known problems.

- **IMPORTANT:** Due to a limitation in the Apple CMM for ColorSync, you must use the Heidelberg CMM when using Device Link profiles (default in Iris iPROOF). You can change this setting in your ColorSync Control Panel.
- If a print job is canceled after the printer runs out of media, a piece of media must be put into the printer in order for the job to properly cancel.
- If the error light on the printer is on when the Iris iPROOF application is launched, the error is not reported to the user.

The Iris iPROOF Product Team *- September 25, 2000*

© Copyright 2000, Iris Graphics, Inc. All rights reserved.

CreoScitex