TIFF/IT Update

(Upd_Brisque4_97_Tiffit - 4.0.97.2)

(Size 2870KB)

Read Me Contents:

A. Who should load this update?
B. What this update includes?
C. Minimum Requirements
D. Loading Instructions

A. Who should load this update?

Customers who are sending TIFF/IT files to Shira station (ScatterProof).

B. What this update includes?

Correct a problem where a TIFF/IT file sent to the Kodak Approval via ScatterProof 1.1 (Shira software developed for Kodak). The ScaterProof software refuses to add the TIFF/IT file into its queue with "Invalid image format" message. The .ict file is OK and the .ifp and .ilw are giving the above problem.

C. Minimum Requirements:

Should be loaded on top of Brisque version 4.0.97 with the mandatory updates **Upd_Brisque4_97_1 (4.0.97.18)** and **Upd_Brisque4_97_ResetBoard (4.0.97.4)**, both exist on Version 4.0.97 2 of 2 CD and are automatically loaded during the Version 4.0.97 installation process.

Select **Station Info > More Info** and make sure you have the following packages prior to installation:

Upd_Brisque4_97_1 (4.0.97.18)
Upd_Brisque4_97_ResetBoard (4.0.97.4)

D. Loading Instructions

Note: If you have previously downloaded the **update.tar** script and created the **.updates** folder, start at **step 3**.

1. Create a folder on the Brisque named **.updates** under the **FIRST** dataVolumes (example: **/dataVolumes/brisque1.1.0/.updates**
   Note: In order to see the **.updates** folder from the Brisque, click View and make sure Show Hidden Objects is selected (or Ctrl + S).
2. Copy/download the script **update.tar** from: ftp://ftpcsa.creo.com/brisque/download/V4/Updates/4.0.97/script/ into the **.updates** folder.
3. Copy/download **Upd_Brisque4_97_Tiffit_2.tar** from: ftp://ftpcsa.creo.com/brisque/download/V4/Updates/4.0.97/Tiffit-2/ into the **.updates** folder.
4. Logout from the Brisque application.
5. Login as root/ripro.
   Note: If you've previously installed the **update.tar** script, continue with **step 7**.
6. Type: ***tar -xvf /dataVolumes/brisque1.1.0/.updates/update.tar*** and hit **Enter**.
7. Type: ***update.sh*** and hit **Enter**.
8. Type a period (**.**) in **INPUT device** field and hit **Enter**.
9. Hit [**F4**], select **Upd_Brisque4_97_Tiffit** and hit **Enter**.
10. Hit **Enter** twice.
11. After the **OK** message, hit the [**F10**] key.
12. Type: **y** and hit **Enter** for automatic reboot.

After rebooting, login as ***cdesci*** and go to **Station Info** --> **More Info** to confirm that:
Upd_Brisque4_97_Tiffit.obj 4.0.97.2 is listed.