Demo Mode Release Notes

English

Prinergy Evo

739-00219A-EN-A

Copyright

Copyright © 2005 Creo Inc. All rights reserved. The Creo wordmark, Creo logo, and the names of the Creo products and services referred to in this document are trademarks of Creo Inc.

Adobe, Acrobat, Adobe Illustrator, Distiller, Photoshop, PostScript, and PageMaker are trademarks of Adobe Systems Incorporated. Apple, iMac, Power Macintosh, AppleShare, AppleTalk, TrueType, ImageWriter, and ImageWriter are registered trademarks of Apple Computer, Inc. Macintosh is a trademark of Apple Computer, Inc., registered in the U.S.A. and other countries. PANTONE, Hexachrome, PANTONE Hexachrome, and PANTONE MATCHING SYSTEM are the property of Pantone, Inc. PEARL, PEARLsetter, PEARLhdp, PEARLdry, and PEARLgold are registered trademarks of Presstek, Inc. Xerox, DocuColor, and MajestiK Color Series are trademarks of Xerox Corporation in the U.S. and/or other countries. Other brand or product names are the trademarks or registered trademarks of their respective owners.

No copying, distribution, publication, modification, or incorporation of this document, in whole or part, is permitted without the express written permission of Creo Inc. In the event of any permitted copying, distribution, publication, modification, or incorporation of this document, no changes in or deletion of author attribution, trademark legend, or copyright notice shall be made. No part of this document may be reproduced, stored in a retrieval system, published, used for commercial exploitation, or transmitted, in any form by any means, electronic, mechanical, photocopying, recording, or otherwise, without the express written permission of Creo Inc. This document is distributed in Adobe Systems Incorporated's PDF (Portable Document Format). You may reproduce the document from the PDF file for internal use. Copies produced from the PDF file must be reproduced in whole.

Creo Inc.
3700 Gilmore Way
Burnaby, B.C., Canada
V5G 4M1
Tel: +1.604.451.2700
Fax:+1.604.437.9891

http://www.creo.com

739-00219A-EN-A

Revised August 2005

Contents

Demo Mode Release Notes 1

Introduction 1
Distribution 1
Demonstration Kit 1
Limitations 2
Minimum System Requirements 2
Installation Notes 3
Step 1: Installing the Microsoft Loopback Adapter 3
Step 2: Installing Prinergy Evo 4
Step 3: Using the Demo Mode Configuration Files 4
Step 4: Typing the Demo Mode License Key 4

Demo Mode Release Notes

Introduction

Prinergy® Evo Demo Mode is intended as a learning and sales aid for Kodak® and Kodak resellers. It allows sales and technical consultants to install Prinergy Evo on their laptops for demonstration and testing purposes. Prinergy Evo in Demo Mode is fully functional and allows you to fully explore the user interface and test Prinergy Evo's PDF processing capabilities. Prinergy Evo Demo Mode is not intended for use in production. Although processing is the same, the output is watermarked.

To minimize memory and processing resources on laptop computers, some features are not licensed.

Prinergy Evo Demo Mode is not intended for distribution to end users for product evaluation.

Distribution

As part of our license agreement with Adobe®, Kodak must track the distribution of Prinergy Evo licenses.

Please do not redistribute without prior written permission from Kodak.

Demonstration Kit

The Prinergy Evo demonstration kit includes:

1. Prinergy Evo software kit
    a. Prinergy Evo software
    b. Supporting documentation:
        - *Prinergy Evo Quick Reference Card*
        - *Prinergy Evo Installation Guide* and *Prinergy Evo System Administration Guide*
    c. Training material:
        - Learning guide
        - Web-based training
        - Learning paths
        - Task Activity Guides with activity files

2. Prinergy Evo Demo Mode license key—three-month demo license
3. Backup of Prinergy Evo Demo Configuration—allow you to easily restore demo configuration
4. Demonstration files
5. Demonstration script

Limitations

The following options are *not* included in the Demo Mode license in order to minimize memory and processing footprints:

- Copydot Tonal Calibration
- Copydot Resampling and Descreening
- CT/LW & TIFF/IT Input
- CT/LW & TIFF/IT Output
- TIFF Downloader
- Hi-resolution output—resolution is restricted to 720 dpi
- Standard and Advanced Trap Editor. The Advanced batch trapper and trap viewer *are* included.
- Acrobat® plug-ins that use Floating License Manager (merge and compare, DotShop™, Preps®, and so on)
- CJK font bundles

Minimum System Requirements

- Microsoft® Windows® 2000 Server or Windows 2003 Server or Windows® XP
- Intel® Pentium® III with 500 MHz or higher processor clock speed, (Pentium 4 with 500 MHz recommended)
- 512 MB of RAM or (1 GB recommend or higher recommended)
- 4 GB of available hard disk space
- Super VGA (800 x 600) or higher-resolution video adapter and monitor
- DVD-ROM drive
- Active network interface 100baseT or higher (or Microsoft Loopback adapter)

Installation Notes

These installation notes are supplementary to the *Prinergy Evo Installation Guide* located on the Prinergy Evo DVD.

- You must be logged in as an Administrator. If you're installing on Windows XP, log on using the Administrative account you plan to use for Prinergy Evo.
- Prinergy Evo requires an active network interface. Windows detects and disables the network interface if the network cable is unplugged. To overcome this, you can use a hardware loopback cable or install Microsoft's Loopback adapter.

Complete the four following steps.

Step 1: Installing the Microsoft Loopback Adapter

Install the Microsoft Loopback adapter on the same computer that will run the Prinergy Evo Administrator and client software.

To install Microsoft Loopback adapter on Windows 2003 Server or XP:

1. Select **Start > Settings > Control Panel.**
2. Double-click **Add Hardware** and then click **Next.**
3. Select **Yes, I have already connected the hardware** and then click **Next.**
4. At the bottom of the list, select **Add a new hardware device** and then click **Next.**
5. Select **Install the hardware that I manually select from a list (Advanced)** and then click **Next.**
6. Select **Network adapters** and then click **Next.**
7. In the **Manufacturer** list, select **Microsoft.**
8. In the **Network Adapter** list, select **Microsoft Loopback adapter,** and then click **Next.**
9. Click **Next** again.
10. Click **Finish.**

To install Microsoft Loopback adapter on Windows 2000 Server:

1. Select **Start > Settings > Control Panel.**
2. Double-click **Add/Remove Hardware** and click **Next.**
3. Select **Add/Troubleshooting a device** and click **Next.**
4. In the list, select **Add a new device** and then click **Next.**
5. Select **No, I want to select the hardware from a list** and click **Next.**
6. Select **Network adapters** and click **Next.**
7. In the **Manufacturer** list, select **Microsoft.**
8. In the **Network Adapter** list, select **Microsoft Loopback adapter,** and then click **Next.**

9. Click **Next** again.
10. Click **Finish.**

Step 2: Installing Prinergy Evo

Using the Prinergy Evo DVD, install Prinergy Evo so that the server and client are on the same Windows computer. When the Prinergy Evo installer prompts you to insert the USB dongle, click **Cancel** to proceed (Demo Mode does not require a dongle). Once the installation is complete, you must type the Demo Mode license key to activate Demo Mode. For more information, see *"Step 4: Typing the Demo Mode License Key" on page 4*.

Step 3: Using the Demo Mode Configuration Files

1. Open Prinergy Evo Administrator.
2. In the Prinergy Evo Administrator dialog box, click the **System** tab and click **Stop**.

   By default, Prinergy Evo finishes its current processing before stopping the system.
3. In the Prinergy Evo Shutdown dialog box, set the parameters as required.
4. Click **Stop Now** to stop Prinergy Evo processes based on the parameters you set.

   Prinergy Evo normally takes at least one minute to stop. Click **Force Quit** only for emergencies where the system appears to be indefinitely stopped.
5. From the Prinergy Evo DVD, copy **DemoMode-Config-1.2.zip** file from **Demo\Support Files** folder to your local hard drive
6. Click the **Save/Restore** tab.
7. Click **Restore.**
8. Locate **DemoMode-Config-1.2.zip** from your hard drive.
9. Click **Restore Now.**
10. Click **No** to restoring license key from backup.

    Prinergy Evo restores the configuration settings and deletes the current configuration settings.

Step 4: Typing the Demo Mode License Key

1. Click the **License** tab and click **Manage Keys.**
2. In **Prinergy Evo License Manager**, click **Add.**
3. Type the Demo Mode license key (you should have received a key with these Release Notes) and click **Apply.**